

mx-188

8x8 DVI Matrix Switcher

The mx-188S DVI Matrix Switcher provides the most flexible and cost effective solution in the market to route high definition video sources plus multi-channel (up to 7.1 channel) digital audio from any of the eight DVI/HDMI sources to the any eight displays at the same time.



Features

- Allows any source to be displayed on multiple displays at the same time
- DVI 1.0 compatible (Single-link)
- Allows any DVI display to view any DVI source at any time
- Supports 7.1 channel digital audio
- Supports default DVI EDID and learns the EDID of displays
- The matrix master can switch every output channels to any DVI inputs by push-in button, IR remote controller or RS-232 control
- Easy installation with rack-mounting
- Fast response time – 2~4 seconds for channel switch

Technical Specifications

Role of Use: Matrix Switcher
 Output Displays: 8x DVI
 Video Support: VGA (640x480) - WUXGA (1920x1200) - 480p-1080p
 DVI Compliance: 1.0
 Video Bandwidth: Single-link 165MHz [4.95Gbps]
 Input: 8x DVI + 1x RS-232 + 1x Ethernet

MECHANICAL

Dimensions (LxWxH): 1RU - 440x96x44mm
 Weight: 6.0lbs
 Power Supply: AC Power 100-240V
 Power consumption: 60 Watts Max
 Operation temperature: 0-40 C
 Relative humidity: 20-90% RH

